



### Grouping

On the driver, select which group you want to assign the luminaires by use of the dip switches.

### Pairing

Press and hold the pair button, the red light will flash quickly. While holding down the pair button, connect the luminaire to the powergrid, then release the pair button. The luminaires are now paired with the remote control. To unpair do the same with the unpair button.

### Choose a group

The settings for choosing a group are matched with the settings on the driver. 1 Stands for A, 2 for B, 3 for C etc. If you want to adjust a setting for the whole group, select the group on the remote control and adjust the desired light quantity or color temperature.

### Adjust color temperature

Adjust the color temperature from a minimum (2300K) to a maximum (4000K) or do this gradually

### Light quantity

Adjust the amount of light from minimum to maximum or do this gradually.

### Preset color temperature

Under this button fixed color temperatures are programmed, 2300K, 2700K, 3000K and 4000K.

### Night mode

The night mode button sets the luminaires to the minimum brightness (2300K).

### Personal settings

Set own preferences under this button. Set the luminaire to the desired color temperature and brightness and then keep the button pressed for a few seconds. The setting is then saved.